UNITED STATES PATENT APPLICATION
FOR GRANT OF LETTERS PATENT

Dayong Chen
Leonard Lee
INVENTOR(S)

TX DETECTION METHOD WITH HIGH SUCCESS PROBABILITY

DTX DETECTION METHOD WITH HIGH SUCCESS PROBABILITY

BACKGROUND OF THE INVENTION

The present invention relates generally to the field of wireless communications, and specifically to a method for discriminating between normal and truncated bursts in

5   discontinuous transmission mode communications.

Discontinuous transmission (DTX) is a technique commonly used in wireless communications systems to reduce interference and conserve battery power. In conventional mobile communication networks, the mobile terminal transmits continuously on the uplink during a call. Normal conversation, however, contains a

10   number of pauses between periods of speech, such as when a user listens to the other party. When a mobile terminal user is not speaking, transmission of the radio signal is not required from an information point of view. With discontinuous transmission, pauses in normal speech are detected in order to suspend radio transmission for the duration of the pause. Discontinuous transmission is typically an optional feature that can be

15   enabled or disabled by the network as required. When used, discontinuous transmission can reduce air traffic, reduce interference between users, and extend battery life in mobile terminals.

During the periods during which no voice activity is detected, a transmitter may transmit nothing, or may transmit truncated bursts containing only radio control

20   information. The transmission of at least some truncated bursts is desirable, to maintain a connection between the mobile terminal and the base station serving it, and to transmit control information. In either case, the state in which truncated bursts are transmitted is known as a DTX-low state; the state in which normal, full-length bursts are transmitted is known as a DTX-high state. The respective formats of a DTX-high, or normal, burst

containing voice or data along with control information, and a DTX-low, or truncated,

burst containing only control information, typically differ significantly. The wireless

system receiver should be able to distinguish between the two, as the two types of burst

transmissions are formatted differently, and the speech decoder will perform different

5   operations based on whether the received data contains speech or random noise.

Several methods are known in the art for determining whether a received DTX

burst is a normal burst or a truncated burst. Two examples of such methods are the use

of Viterbi decoding metric and an estimated Bit Error Rate (BER) as the detection

criteria. However, both methods suffer from poor DTX detection probability in high noise

10   environments, *i.e.*, when the Carrier-to-Interference Ratio (C/I) is low, or under high

Rayleigh fading. At low C/I, both detection methods suffer from noise. For example, the

Viterbi decoding metric can be an unreliable indicator if the correct path in the trellis

corresponding to the correct code word is eliminated during channel decoding due to

long bit error bursts in the received data. Similarly, the estimated BER is not necessarily

15   the actual BER, as the receiver estimates the BER by re-encoding decoded data and

then comparing the re-encoded data with the data originally received. Since the ·

decoded data may have many residual bit errors after decoding, the re-encoded data

may be similarly erroneous, and will result in incorrect BER estimates when compared

with the received data. Statistically, the probability distributions of either detection

20   method on normal and DTX truncated bursts overlap considerably, causing high

detection error.

SUMMARY OF THE INVENTION

The present invention relates to a method of classifying a received data frame as

belonging to one of a plurality of possible classes, each class having corresponding

25   formats wherein a known bit pattern is located in different respective positions within the

2

data frame. In one embodiment, the method comprises receiving the frame, computing

a first value representing a confidence-weighted correlation between the known bit

pattern and data from a first position of the frame, and classifying the frame as belonging

to a first class or a second class based on the first value. The first value may be the

5   Euclidean distance between a soft bit representation of a reference CDVCC and the

received frame data bits corresponding to the position of the CDVCC in a normal burst.

The classes may represent DTX normal and truncated bursts.

In another embodiment, the method further comprises computing a second value

representing a confidence-weighted correlation between the known bit pattern and data

10   from a second position of the frame different the first position, and classifying the frame

additionally based on the second value. The second value may be the Euclidean

distance between a soft bit representation of the reference CDVCC and the received

frame data bits corresponding to the position of the CDVCC in a truncated burst. A ratio

of the first value to the second value may be calculated and compared to a

15   predetermined threshold to classify the DTX state of the frame.

In another embodiment, the method further comprises calculating normalized

first and second values by dividing the values by a measured parameter. The

normalized values are compared to a predetermined thresholding function to classify the

frame. One example of the measured parameter is the maximum of average RSSI over

20   the received frame measured at each diversity receive antenna. The predetermined

thresholding function is calculated to minimize the probability of false classification, and

may comprise a piece-wise linear curve.

BRIEF DESCRIPTION OF DRAWINGS

Figure 1 depicts the formats of normal and truncated bursts, and the comparison

25   method of the present invention as relates to a received burst;

Figure 2 is a plot of the probability distributions for normal and truncated bursts using D1 to classify the bursts, in a low-noise environment;

Figure 3 is a flowchart depicting the method steps of one embodiment of the present invention;

5   Figure 4 is a plot of the probability distributions for normal and truncated bursts using D1 to classify the bursts, in a high-noise environment;

Figure 5 is a plot of the probability distributions for normal and truncated bursts using the ratio D1/D2 to classify the bursts, in a high-noise environment;

Figure 6 is a scatterplot of normalized D1, D2 points under a variety of channel

10   conditions, and a piece-wise linear thresholding function; and

Figure 7 is a flowchart depicting the method steps of two embodiments of the present invention.

DETAILED DESCRIPTION OF THE INVENTION

The present invention is described herein with reference to the

15   Telecommunications Industry Association (TIA) / Electronics Industry Alliance (EIA) standard TIA/EIA-136, which is incorporated herein by reference. The TIA/EIA-136 standard is a Time Division Multiple Access (TDMA) standard for cellular and personal communication services (PCS) networks. The present invention is not thus limited, however, and may also find utility in a cellular/PCS communication network based on

20   Code Division Multiple Access (CDMA), such as IS-95, cdma2000, and Wideband CDMA (W-CDMA), or a broad variety of other wireless communications technologies and protocols.

Discontinuous transmission (DTX) is a technique used to reduce overall interference in the air interface. Particularly in CDMA technology wireless

25   communications systems, a reduction in interference in the air interface can increase

4

system capacity. DTX can also conserve power in mobile terminals. A conventional

mobile terminal transmits continuously on the uplink whenever a call is in progress.

Continuous transmission on the uplink, however, is inefficient since normal speech

contains a number of pauses, for example, when the mobile terminal user is not

5   speaking. Continuing transmission during such pauses conveys no useful information.

The concept underlying DTX is to reduce interference and conserve power by switching

off the transmitter during periods when speech is not present. When DTX is enabled,

the mobile terminal switches between transmitting a normal burst (DTX High) during

periods of user speech, and transmitting a truncated burst (DTX Low) during speech

10   pauses.

Figure 1 depicts the data formats of a normal burst 10 and a truncated burst 12.

The normal burst 10, comprising 324 bits, includes six Guard and Ramp bits 16, a 16-bit

first data field 18, a 28-bit Training Sequence 20, a 128-bit second data field 22, a 12-bit

Slow Associated Control Channel (SACCH) subframe 24, a 12-bit Coded Digital

15   Verification Color Code (CDVCC) 26, and a 128-bit third data field 28. These various

data bits and sub-frame fields are defined in the aforementioned wireless

communications standard, are well known to those of skill in the art, and are not further

explicated herein. The truncated burst 12, comprising 68 bits, includes the six Guard

and Ramp bits 16, a 4-bit reserved field 32, the 12-bit SACCH sub-frame 34, the 28-bit

20   Training Sequence 20, and the 12-bit CDVCC sub-frame 38. Note that the truncated

burst SACCH sub-frame 34 and the truncated burst CDVCC sub-frame 38 occupy

different positions within the frame than these same data fields occupy within the normal

burst 10 (*i.e.*, SACCH 24 and CDVCC 26). The presence of the SACCH sub-frame 34 in

the truncated burst 12, in a different position than in the normal burst 10, makes the

25   correct DTX state detection (*i.e.*, DTX-high or DTX-low) desirable. In the case of an

erroneous DTX detection, a very high bit error rate will be introduced into the received

SACCH sub-frame, resulting in degradation of the overall SACCH performance.

On the other hand, it is the differing location of the CDVCC sub-field within the normal burst 10 and the truncated burst 12 that is exploited by the present invention to achieve a DTX detection with a high success probability, even under low C/I conditions.

5   The CDVCC is a unique 12-bit code word used to identify the base station (or sector thereof) that is handling a call for a mobile terminal. The CDVCC is communicated to the mobile terminal at the call initiation (or handoff) and the mobile terminal returns the CDVCC in its uplink transmissions. The CDVCC is hence a known value, depicted in Figure 1 as the Reference value, CDVCC_R 40. According to the present invention, the

10   CDVCC_R 40 is compared to up to two positions of a received burst 14 – the bit positions corresponding to the CDVCC_N 26 in a normal burst 10, and optionally the bit positions corresponding to the CDVCC_T 38 in a truncated burst 12. Comparison of these bits yield the quantities D1 and D2, respectively, as described more fully herein.

In one embodiment, an initial determination as to the DTX state of a received

15   burst 14, which under high C/I conditions may be a sufficient one, may be made from the value D1, defined as the Euclidian distance between the demodulated soft bits of the CDVCC_N 26 and a soft bit representation of the reference CDVCC_R 40. Soft bits are commonly used in wireless communications systems to optimize the decoder performance. As used herein, the term "soft bit" indicates both the binary value of a

20   demodulated bit and the confidence that the demodulation was performed correctly. For example, the output of a demodulator is typically in a soft bit format. The sign of the soft bit (i.e., a positive or negative voltage level) may indicate the binary value (i.e., 1 or 0). The magnitude of the soft bit, for example a voltage level, may indicate the confidence level that the bit was demodulated correctly. For example, random noise will typically

25   generate soft bits with a value close to 0, with a random excursion in the positive or negative direction. In contrast, bits demodulated from a strong signal in the absence of

comparison of the two bit patterns including both the sign and the magnitude, *i.e.,* considering both correlation and confidence, respectively, is referred to herein as the Euclidean distance between the bit patterns. The Euclidean distance may be calculated as follows:

5   First the CDVCC_R 40 bit pattern is converted to a soft bit format compatible with the demodulated CDVCC_N 26 soft bits. Let CDVCC_R$_i$ be the i-th bit of CDVCC_R 40, where i equals 1, 2, ... 12. Each bit of the CDVCC_R 40 is converted to the corresponding ideal soft bit SCDVCC_R$_i$ according to the following equation:

$$SCDVCC\_R_i = \begin{cases} MAX\_SOFT & \text{if CDVCC\_R}_i = 1 \\ \\ -MAX\_SOFT & \text{if CDVCC\_R}_i = 0 \end{cases} \tag{1}$$

Second, let CDVCC_N$_i$ be the i-th demodulated soft bit of CDVCC_N 26. The

10 average Euclidian distance D1 between the received CDVCC_N 26 and the soft bit format reference SCDVCC_R 40 is calculated according to the following equation:

$$D1 = \sqrt{\sum_{i=1}^{12}(CDVCC\_N_i - SCDVCC\_R_i)^2} \tag{2}$$

If the received burst 14 was a normal burst 10, the signs of CDVCC_N 26 are correlated with the bits of the CDVCC_R 40, and additionally the magnitudes of the

15 CDVCC_N 26 soft bits will tend to be close to MAX_SOFT, making D1 small. On the other hand, if the received burst 14 was a truncated burst 12, there will be very low correlation between the signs of the CDVCC_N 26 and the bits of the CDVCC_R 40. Additionally, the magnitudes of the CDVCC_N 26 soft bits will be on average much smaller compared with MAX_SOFT, making D1 large.

20   Figure 2 depicts a graph showing the D1 probability distribution of the classification of a large number of received bursts 14 as normal bursts 10, indicated by

the dotted line, or truncated bursts 12, indicated by the dashed line, classified by inspection of only D1. The probability distributions represent the envelope of histograms of simulations of large numbers of normal and truncated bursts. The probabilities plotted in Figure 2 are for received bursts 14 simulated under a low noise environment, with a

5   C/I of 20 dB. The two probability distributions show adequate separation, and indicate that inspection of D1 alone is sufficient to classify a received burst 14 as being a normal burst 10 or a truncated burst 12, with a high probability of success. In practice, D1 may be compared to a predetermined threshold value T, chosen to lie between the probability distributions for normal and truncated bursts, as determined through simulations. If D1 <

10   T, a normal burst 10 is indicated; if D1 ≥ T, a truncated burst 14 was received.

The method of classifying a received burst 14 as a normal burst 10 or truncated burst 14 comparison of D1 to T is depicted in flowchart form in Figure 3. Initially, the threshold T is determined (block 42), such as through simulation, and is programmed into a receiver at the factory or in a field upgrade. When communication is established

15   between a mobile terminal and a base station (or sector thereof), and a CDVCC is assigned, the soft bit representation SCDVCC_R may be calculated (block 44). The classification methods begin when a burst 14 of unknown DTX state is received by the receiver (block 46). The reference CDVCC_R 40 is compared to the CDVCC_N 26, and the Euclidean distance D1 is calculated (block 48). D1 is compared to the threshold T,

20   and the received burst 14 is classified as a normal burst 10 or truncated burst 14 (block 50).

Under favorable noise conditions, D1 may be sufficient to enable successful DTX classification. Figure 4, however, depicts a graph of the same probability distributions as those of Figure 2, but calculated under a high noise environment, with a C/I of only 5 dB.

25   Figure 4 indicates a considerable overlap between the probability distributions for a normal burst 10 and a truncated burst 12. Values of D1 for a given received burst 14

9

that fall within this range of overlap cannot be classified as arising from a normal burst 10 or a truncated burst 14 with any reasonable probability of success. Thus, inspection of D1 alone is insufficient to positively categorize the received burst 14 in a low C/I environment.

5   Consequently, according to one embodiment of the present invention, the two distributions depicted in Figures 2 and 4 may be further separated, even under very low C/I conditions, by calculating and considering a second Euclidian distance D2. D2 is the Euclidian distance between the bit positions of the received burst 14 that correspond to the CDVCC_T 38 of a truncated burst 12 and the reference CDVCC_R 40. D2 is

10   calculated in much the same manner as D1, substituting the soft bits representing CDVCC_T 38 for the soft bits representing CDVCC_N 26. Soft bits $SCDVCC\_R_i$ representing an ideal soft bit representation of CDVCC_R 40, are calculated as above, according to equation (1). The equation for the Euclidian distance D2 is thus:

$$D2 = \sqrt{\sum_{i=1}^{12} (CDVCC\_T_i - SCDVCC\_R_i)^2} \qquad (3)$$

15   Regardless of whether a normal burst 10 or a truncated burst 12 has been demodulated, the magnitudes of the CDVCC_T 38 soft bits have the same statistics, since in both cases actual signals were transmitted during the time slot allocated to the CDVCC 38. For truncated bursts 12, the signs of the CDVCC_T 38 soft bits will be correlated with the signs of the soft bits SCDVCCR, since the binary value CDVCC_R 40

20   was actually transmitted during the CDVCC_T 38 time slot, making D2 small. However, for normal bursts 10, the signs of the CDVCC_T 38 soft bits are random, since the data transmitted during the CDVCC_T 38 time interval is part of the speech frame, making D2 large.

The final DTX state detection for the received burst 14 is based on the ratio R

25   between D1 and D2,

$$R = \frac{D1}{D2}$$ (4)

From the explanations above considering the trends of D1 and D2, it follows that R tends to be small for normal bursts 10, since in the case of a normal burst 10, D1 tends to be small while D2 tends to be large. The opposite is true for truncated bursts

5   14; R tends to be large since D1 tends to be large while D2 tends to be small. In general, the probability distributions for R in the case of a normal burst 10 and a truncated burst 12 tend to exhibit greater separation and less overlap than the corresponding D1 distributions, under the same C/I environment. This significantly increases the probability of a successful DTX state detection. This result is depicted in

10   Figure 5, showing the probability distributions of R in the case of a normal burst 10 (dotted line) and a truncated burst 12 (dashed line) for a noise environment identical to that depicted in Figure 4, *i.e.*, a C/I of 5 dB.

A simple DTX classification using the ratio R may be performed by comparing R to a predetermined threshold T. If R is greater than or equal to T, the received burst 14

15   is classified as a truncated burst 12. If R is less than T, a normal burst 10 was received. The value of T is chosen to be in the region where the two probability distributions overlap. As discussed above, with increasing C/I, the probability distributions exhibit greater separation, allowing greater flexibility in the threshold T. Conversely, as the C/I decreases, the overlap of the two distributions increases. Since the noise environment

20   cannot be known *a priori*, a single threshold value T must be chosen, which is generally a value T that will give reasonable performance under worst case conditions. Once selected, the value of the threshold T will typically remain static, as adaptive thresholding is computationally intensive, and under unusual conditions can cause a value T to be selected that yields erroneous classifications.

25   In one embodiment of the present invention, the thresholding function for the

11

classification of a received burst 14 as being a normal burst 10 or a truncated burst 12 is not a single value T, but rather a two-dimensional curve. For any given set of environmental variables (such as for example, the C/I environment, the Doppler values, and various values for the a multipath delay *tau*,), comparison of a received burst 14 to

5   the CDVCC_R 40 will yield values for D1 and D2, as described above. By simulating the transmission of both a normal burst 10 and a truncated burst 12 under each set of conditions, a plurality of D1/D2 value pairs are acquired, which form two clusters – one cluster of values corresponding to the normal bursts 10 and another corresponding to the truncated bursts 12. Plotting the pairs of D1, D2 values in a scatter plot diagram on

10   a graph with D1 as the abscissa and the D2 as the ordinate reveals that a thresholding function that best separates the two cases is not a single value but a two-dimensional curve. The shape of the curve, however, was found to vary significantly according to the C/I environment. Thus, it was determined to normalize the values D1 and D2 by dividing by the average received signal strength indicator (RSSI) on a burst by burst basis. The

15   RSSI parameter is already calculated in the equalizer, and is readily available. In the case of an *n*-way diversity receiver, the RSSI is averaged over the duration of the burst at each leg of the diversity receiver, and the maximum of these *n* average RSSI values is chosen as the normalization factor. This value is referred to herein as the "maximum average RSSI," a term that encompasses simply the average RSSI in a non-diversity

20   receiver. The normalized D1 and D2 values result in consistent classification performance using a single thresholding function over a wide range of C/I values. The normalized D1 and D2 equations are shown below:

$$D1_{Normalized} = \frac{D1}{RSSI_{AVG}} \qquad\qquad (5)$$

$$D2_{Normalized} = \frac{D2}{RSSI_{AVG}} \qquad\qquad (6)$$

Figure 6 depicts a scatter plot diagram of points representing both normal bursts 10 and truncated bursts 12 over a wide variety of environmental conditions. The normalized D1 and normalized D2 values for each set of conditions are plotted. Mathematical analysis of the values of the plotted points to minimize false detection

5   yielded the piece-wise linear curve C used to classify the received burst 14 as being a normal burst 10 or a truncated burst 12. The line segment boundaries were optimized for C/I=[5, 15, 20, 30] dB; Doppler=[7, 77] Hz and *tau*=[0, 4, 8] samples. Under these conditions, the equations of the line segments depicted in Figure 6 were determined to be:

10   line1: $\dfrac{D2}{RSSI_{AVG}} = 1.498 \cdot \dfrac{D1}{RSSI_{AVG}} - 9968$ (7)

line2: $\dfrac{D1}{RSSI_{AVG}} = 60300$ (8)

The above equations and the results plotted in Figure 6 are representative only. In general, any two-dimensional curves C may be utilized for the thresholding function of classifying a received burst 14 as a normal burst 10 or a truncated burst 12. For

15   example, a more complex curve, either comprising a greater number of piece-wise linear segments or a higher order mathematical function, may provide better classification accuracy, at the expense of computational complexity, as will be understood by those of skill in the art.

The methods of the present invention utilizing both D1 and D2, as described

20   above, maximize the separation of probability distributions of the normal burst 10 and truncated burst 12 conditions, even under very low C/I environments. This separation allows for a high probability of success in classifying the DTX state of a received burst 14. The methods are depicted in flowchart form in Figure 7. The initial steps are the same as the method utilizing only D1, depicted in Figure 3. First, the classification

13

threshold T or curve C is determined (block 52), such as through simulation, and is

programmed into a receiver at the factory or in a field upgrade. When communication is

established between a mobile terminal and a base station (or sector thereof), and a

CDVCC is assigned, the soft bit representation SCDVCC_R may be calculated (block

5   54). The classification methods begin when a burst 14 of unknown DTX state is

received by the receiver (block 56). The reference CDVCC_R 40 is compared to the

CDVCC_N 26, and the Euclidean distance D1 is calculated (block 58). To achieve

greater accuracy in classification by additionally comparing the characteristics of the

reference CDVCC_R 40 to the characteristics of the CDVCC_T 38, D2 is calculated

10 (step 60). Since the Euclidian rather than Hamming distance is used in both

comparisons, all information contained in the soft bits, *i.e.*, both binary value and

demodulation confidence, is considered. In one embodiment, the ratio R is calculated

(step 62), and compared to the threshold T (step 64). In another embodiment, the D1

and D2 values are normalized by the maximum RSSI (step 66). The normalized D1, D2

15 values are then compared to a thresholding curve C (step 68). In both methods, the

DTX state classification of the received burst 14 is performed at step 70, with a high

probability of success as compared to prior art classification methods. One of the

methods is then repeated upon receiving a new burst 14 (step 56).

Although the present invention has been described herein with respect to

20 particular features, aspects and embodiments thereof, it will be apparent that numerous

variations, modifications, and other embodiments are possible within the broad scope of

the present invention, and accordingly, all variations, modifications and embodiments

are to be regarded as being within the scope of the invention. The present embodiments

are therefore to be construed in all aspects as illustrative and not restrictive and all

25 changes coming within the meaning and equivalency range of the appended claims are

intended to be embraced therein.